

| Index | Behaviour | Command Word | Reply word | GPIO Pin | Level |
|-------|----------------|--|---|----------|-------|
| 1 | wakeup_uni | Hello Pudding Hey Pudding Ni Hao | I am here please go ahead what can I do for you Yes, I am Listening | - | - |
| 2 | FirstLightOn | Turn on first light First light on Light One On One Light On | First Light turned On | GPIO_B0 | HIGH |
| 3 | FirstLightOff | Turn off first light First light off Light One Off One Light Off | First Light turned Off | GPIO_B0 | LOW |
| 4 | SecondLightOn | Turn on second light Second light on Light Two On Two Light On | Second Light turned On | GPIO_B1 | HIGH |
| 4 | SecondLightOff | Turn off second light Second light off Light Two Off Two Light Off | Second Light turned Off | GPIO_B1 | LOW |
| 5 | ThirdLightOn | Turn on third light third light on Light Three On Three Light On | Third Light turned On | GPIO_B2 | HIGH |
| 6 | ThirdLightOff | Turn off third light third light off Light Three Off Three Light Off | Third Light turned Off | GPIO_B2 | LOW |
| 7 | FourthLightOn | Turn on fourth light fourth light on Light Four On Four Light On | Fourth Light turned On | GPIO_B3 | HIGH |
| 8 | FourthLightOff | Turn off fourth light fourth light off Light Four Off Four Light Off | Fourth Light turned Off | GPIO_B3 | LOW |
| 9 | FanOn | Turn on Fan Turn on the Fan Fan on | Turning on the Fan | GPIO_B7 | LOW |
| | | | | GPIO_B6 | HIGH |
| | | | | GPIO_A27 | LOW |
| 10 | FanSpeed1 | Fan Speed one Fan Speed Minimum | Fan Speed Set to one | GPIO_B7 | HIGH |
| | | | | GPIO_B6 | LOW |
| | | | | GPIO_A27 | LOW |
| 11 | FanSpeed2 | Fan Speed two | Fan Speed Set to Two | GPIO_B7 | LOW |
| | | | | GPIO_B6 | HIGH |
| | | | | GPIO_A27 | LOW |
| 12 | FanSpeed3 | Fan Speed Three | Fan Speed Set to Three | GPIO_B7 | HIGH |
| | | | | GPIO_B6 | HIGH |
| | | | | GPIO_A27 | LOW |
| 13 | FanSpeed4 | Fan Speed Four Fan Speed maximum | Fan Speed Set to Four | GPIO_B7 | LOW |
| | | | | GPIO_B6 | LOW |
| | | | | GPIO_A27 | HIGH |
| 14 | FanOff | Turn off Fan Turn off the Fan Fan off | Turning off the Fan | GPIO_B7 | LOW |
| | | | | GPIO_B6 | LOW |
| | | | | GPIO_A27 | LOW |
| 15 | AllLightsOn | Turn On all the Lights Turn On all Lights All lights On | Turning On all the lights | GPIO_B0 | HIGH |
| | | | | GPIO_B1 | HIGH |
| | | | | GPIO_B2 | HIGH |
| | | | | GPIO_B3 | HIGH |
| 16 | AllLightsOff | Turn Off all the Lights Turn Off all Lights All lights Off | Turn Off all the Lights Turn Off all Lights All lights Off | GPIO_B0 | LOW |
| | | | | GPIO_B1 | LOW |
| | | | | GPIO_B2 | LOW |
| 17 | volumeUpUni | Increase volume Volume up Volume increase | ok, volume increase | - | - |
| 18 | volumeDownUni | decrease volume volume down volume decrease | ok, volume decrease | - | - |
| 19 | volumeMaxUni | volume maximum maximum volume | ok, volume maximum | - | - |
| 20 | volumeMinUni | volume minimum minimum volume | ok, volume minimum | - | - |